



'C' Programmable Application Development Module with Ethernet PTQ-ADMNET

The ProTalk Application Development Ethernet Communication Module is a Quantum backplane compatible module that allows Modicon Quantum processors to interface with protocols that support Ethernet compatible devices and hosts. Devices commonly supporting the protocol include Rockwell Automation PLCs, and host HMI systems.

Features and Benefits

The PTQ-ADMNET module acts as an input/output module between the Ethernet Explicit Messaging network, and the Quantum backplane. Data transfer from the Quantum processor is asynchronous from the actions on the Ethernet network. A 4000-word register space in the module exchanges data between the processor and the Ethernet network.

The PTQ-ADMNET module is a powerful communication interface for Quantum platform processors. Developed under license from Schneider Electric, the module incorporates proprietary backplane technology that enables powerful data access to the Quantum processor.

General Specifications

- Single Slot – Quantum backplane compatible
- The module is recognized as an Options module and has access to PLC memory for data transfer
- Configuration data is stored in non-volatile memory in the ProTalk module
- Up to six modules can be placed in a rack
- Local rack – The module must be placed in the same rack as processor.
- Compatible with common Quantum / Unity programming tools.
- Quantum data types supported: 3x, 4x
- High speed data transfer across backplane provides quick data update times.
- Sample ladder file available.

Hardware Specifications

Specification	Description
Backplane Current Load	800 mA @ 5 V
Operating Temperature	0 to 60°C (32 to 140°F)

'C' Programmable Application Development Module with Ethernet PTQ-ADMNET

The PTQ-ADMNET module is the ideal solution for the many applications where Ethernet connectivity must be added to a Quantum system.

The ADMNET solution is a powerful module designed with both Client and Server support. This broad support enables the module to function as a data collection sub-master, or to be a powerful slave as a remote off an HMI host. Applications for the module are found in most industries, especially Manufacturing, Oil and Gas, Electrical Power and Food processing.

How to Contact Us: Sales and Support

All ProSoft Technology products are backed with unlimited technical support. Contact our worldwide Technical Support team directly by phone or email:

Asia Pacific

+603.7724.2080, asiapc@prosoft-technology.com
Languages spoken include: Chinese, Japanese, English

Europe – Middle East – Africa

+33 (0) 5.34.36.87.20, support.EMEA@prosoft-technology.com
Languages spoken include: French, English

North America

+1.661.716.5100, support@prosoft-technology.com
Languages spoken include: English, Spanish

Latin America (Sales only)

+1.281.298.9109, latinam@prosoft-technology.com
Languages spoken include: Spanish, English

Brasil

+55-11.5084.5178, eduardo@prosoft-technology.com
Languages spoken include: Portuguese, English

Specification	Description
Storage Temperature	-40 to 85°C (-40 to 185°F)
Relative Humidity	5 to 95% (non-condensing)
LED Indicators	Module Status Backplane Transfer Status Serial Port Activity LED Serial Activity and Error LED Status
Configuration Serial Port (PRT1)	DB-9M PC Compatible RS-232 only No hardware handshaking
Application Serial Ports	(PRT2, PRT3) DB-9M PC Compatible RS-232/422/485 jumper selectable RS-422/485 screw termination included RS-232 handshaking configurable 500V Optical isolation from backplane
Application Ethernet port	RJ45 Connector Link and Activity LED indicators

Functional Specifications

The PTQ-ADM API Suite allows software developers access to the top layer of the Quantum backplane and serial ports. The PTQ-ADMNET API suite accesses the Ethernet port.

Both APIs can be easily used without having detailed knowledge of the module's hardware design. The PTQ-ADMNET API Suite consists the Ethernet Port API. The Ethernet Port API provides access to the Ethernet network. Applications for the PTQ-ADMNET module may be developed using industry-standard DOS programming tools and the appropriate API components.

The PTQ-ADMNET module has three serial ports, two of which are isolated for field interfaces, and one Ethernet port.

- CFG -- debug/configuration -- RS-232
- PRT1 -- Application -- RS-232, RS-422 or RS-485
- PRT2 -- Application -- RS-232, RS-422 or RS-485
- Ethernet Port

PRT1 and PRT2 are jumper configured for direct or Multi-drop field communication. The application program can be written to control the two application ports independently, allowing maximum flexibility in the design.

General Protocol Specifications

- Allows software developers to access Quantum / Unity backplane and Serial/Ethernet ports without needing detailed knowledge of the module's hardware design
- API library functions are specified using the C programming language syntax

- Supports multi-threaded applications
- Compatible compilers (16-bit DOS target)
 - Digital Mars C++ V8.49 (included)
 - Borland C++ V5.02
- Operating System – General software DOS 6-XL
- Flash ROM program space: 896 KB
- RAM program and data space: 640 KB
- Compact Flash socket: Up to 64 MB

ADM API Libraries

Each API provides a library of function calls. This library supports any programming language that is compatible with the Pascal calling convention.

- Initialization – Open and close the API
- Debug Port – Debug port user interface
- Database – Read and write data to database
- Timer – Start and check timers
- Backplane – Transfer data over the backplane
- LED – Set user LED indicators
- Flash – Parse configuration files
- Miscellaneous – Configure the console

Additional Products

ProSoft Technology offers a full complement of hardware and software solutions for a wide variety of industrial communication platforms.

Visit our web site at <http://www.prosoft-technology.com> for a complete list of products.

Ordering Information

To order this product, please use the following:

PTQ-ADMNET 'C' Programmable Application Development Module with Ethernet

To place an order, please contact your local ProSoft Technology distributor. For a list of ProSoft distributors near you, go to <http://www.prosoft-technology.com>

Distributors:

Place your order by email or fax to:

North American / Latin American / Asia Pacific
orders@prosoft-technology.com,
fax to +1 661.716.5101

Europe

europe@prosoft-technology.com,
fax to +33 (0) 5.61.78.40.52

Copyright © ProSoft Technology, Inc. 2000 - 2007. All Rights Reserved.

January 30, 2007